# Wireless Outlet Dimmer Looks Small, Thinks Big

The Wireless Outlet Dimmer connects to household plug-in devices, immediately making them part of the home automation system and enabling quick and easy configuration. Its dual-capacity dimmer allows users to independently dim two lights from the single unit. From the living room floor lamp to the bedroom table lamp, the Wireless Outlet Dimmer adds intelligent, automated features to just about any dimmable plug-in device.

It's all part of the Control4 vision. We bring the benefits of a truly automated home to more people with solutions that are affordable, easy to install and designed to adapt to any home or lifestyle.

# Features and Benefits

#### Smart Design

- Small form factor With its inconspicuous design and sleek finish, it's virtually unnoticeable.
- Low profile Sits flush against the wall so it can fit behind furniture.
- $\bullet$  Dual outlets Two dimmable outlets give added flexibility.
- **Secure mounting** Special screw tab design allows for the Outlet Dimmer to be securely attached to the wall outlet. It won't accidentally be unplugged.

### Easy To Install and Use

- Wireless No special cables to pull through the home.
- Easy recognition Just plug it in, press a button, and it's immediately recognized.
- Easily controllable Immediately controllable and easily updateable from a Control4 Keypad, Touch Screen, or System Remote Control.

#### Intelligent From Front To Back

- Built-in dimmer capabilities Dim lamps for a romantic dinner or set bedroom lamps to gradually turn on in the morning.
- Anytime control Adjust the room's brightness level based on the time of day.
- Anywhere control Intelligent, reliable, wireless connectivity using the ZigBee<sup>™</sup> (802.15.4) mesh networking standard.
- Energy Efficient By automating plug-in devices, electricity is only used when needed.

**Dim** the floor lamps in the living room when your house goes to sleep. In the morning **gently light** your children's bedroom with light from a table lamp. **Ramp** up the desk lamp in the den as you enter the room.



# Wireless Outlet Dimmer



## **Technical Specifications**

#### Model Number

• LOZ-5D1-W

### Load Capacity

400 Watts shared by both outlets

#### Load Type

- All Incandescent/Halogen
- $\bullet$  All dimmable magnetic low-voltage with 75% or greater load factor
- All dimmable electronic low-voltage with 75% or greater load factor

#### Communications

• Wireless ZigBee (802.15.4) mesh networking

#### Environmental

- Operational 0°C to 40°C
- Humidity 5% to 95% Non-Condensing
- $\bullet$  Storage -20°C to 70°C

#### Power Requirements

• 120 VAC +/- 30% (84-156 VAC) 50 or 60 Hertz

#### **Dimensions & Weight**

- H x W x D: 4.5" x 2.6" x 1.6"
- 115mm x 67mm x 42mm
- Weight: 8.0oz
  - 22

#### **Available Colors**

• White

## The Control4 Wireless Outlet Family

In addition to the Wireless Outlet Dimmer, Control4 offers:



Wireless Outlet Switch — A controllable switch for plug-in devices rated up to 15 amps.

## **Related Control4 Products**

In addition to the Wireless Outlet Dimmer, Control4 offers:



3-Way Switch — For new or retrofit home automation solutions using ZigBee wireless connectivity.



©2004 Control4. All rights reserved. Control4 and the Control4 logo are registered trademarks. All other trademarks are property of their respective owners. 03-0305